

12) Dryer blower motor and heater will activate for **10** seconds to check amps When cycle is complete, you will hear 2 long Beeps. This is the indication that the test cycle has finished.

Note: During this test cycle, if the Control board senses a failure that it is programmed to monitor, it will display an error code.

-			
1	1		Moisture sensor disconnect
1	2		Motor Control Status Error
1	3		Motor Control Comms Error
1	4		Diverter Timeout
1	5		Drain Error (pressure sensor models)
2	1		Pressure Sensor Disconnect Error
2	2		Fill Error (pressure sensor models
2	3		Low Level Error
2	4		High Level Error
2	5		Level Sensor Error
3	1		User Interface - Main Control Communication Error
3	2	YES	Pump Flow Error
3	3		Drain Pump Error
3	4		Motor Status Error
3	5		Motor Undervoltage Error
4	1		Temperature Sensor Error
4	2	YES	Wash Heater Error
4	3	YES	Dispenser Error
4	4	YES	Inlet Valve Error
4	5		
5	1	YES	Vent Error
5	2	YES	Blower Error
5	3	YES	Dry Heater Error
5	4	YES	Current Sense Error
5	5		Internal Error
Flash both LED1 and LED2			Moisture Sensor - water detection
Flash all LEDs but start and run continuously			AC Power Loss